

PM3-24V LK SERIES

WITH STATE-OF-THE-ART 3 STAGE SMART CHARGING TECHNOLOGY AND ADJUSTABLE POWER SUPPLY MODE. POWERMAX POWER CONVERTER/BATTERY CHARGERS ARE ENGINEERED WITH THE USER AND VARIABLE ENVIRONMENTAL CONDITIONS IN MIND.

STANDARD FEATURES INCLUDE:

- 3 STAGE SMART CHARGING
- FIXED POWER SUPPLY MODE
- VARIABLE VOLTAGE ADJUSTMENT 26Vdc TO 33Vdc
- WORKS WITH ANY BATTERY TYPE
- LED STATUS INDICATOR LIGHT
- INTERNALLY MOUNTED COOLING FAN
- 2 YEAR WARRANTY



**P
W
E
R
M
A
X**

MODEL NUMBER	PM3-25-24LK	PM3-30-24LK	PM3-40-24LK	PM3-50-24LK
DC OUTPUT VOLTAGE (NO LOAD) APPROX.	29.2/27.2/26.4V	29.2/27.2/26.4V	29.2/27.2/26.4V	29.2/27.2/26.4V
MAX AMP OUTPUT CONTINUOUS	25 amps	30 amps	40 amps	50 amps
MAX POWER OUTPUT CONTINUOUS	730 watts	876 watts	1168 watts	1460 watts
MAX AC CURRENT	7.5 Amps	9 Amps	12 Amps	14 Amps
TYPICAL EFFICIENCY	>85%	>85%	>85%	>85%
FAN CONTROL	Proportional	Proportional	Proportional	Proportional
SHORT CIRCUIT, OVERLOAD THERMAL PROTECTION	Yes	Yes	Yes	Yes
DIMENSIONS	7.8 x 9.5 x 3.5	7.8 x 9.5 x 3.5	7.8 x 9.5 x 3.5	7.8 x 9.5 x 3.5
WEIGHT	7.0 lbs	7.0 lbs	8.0 lbs	9.0 lbs

**BATTERY CHARGERS
POWER SUPPLIES
AC-DC CONVERTERS
DC-DC CONVERTERS
AUTOMATIC TRANSFER SWITCHES**

**20 YEARS EXPERIENCE.
POWERMAX PM3 ARE INDUSTRY STANDARD.
SUPPLYING OVER 20 DIFFERENT INDUSTRIES**

**(941) 201-8041
POWERMAXCONVERTERS.COM**