

Schauer® Battery Chargers

Schauer is a trademark of the Brookwood Group Inc.



Schauer
3210 Wasson Road
Cincinnati, Ohio 45209

1-800-899-VOLT (8658)

Fax: 1-513-791-7192

www.battery-chargers.com

MODEL JAC2512, JAC2024H, JAC3024

Fully Automatic Multimode Electronic Charger

Intelligent chargers follow battery impedance to end of charge cycle for all battery types. Fully automatic.

Red LED indicates AC power on, yellow LED indicates battery is charging, green LED indicates float mode.

- Charge control: constant current charge to a constant voltage, then to a float standby voltage.
- Current limiting.
- Fully automatic 3 stage charger can be left on the battery in maintaining/float mode.
- Can be set for any type lead acid battery, including conventional, maintenance free, deep cycle, gelled-type, valve regulated batteries.
- Cyclic Voltage: Flooded 2.47 volts/cell; Gel & AGM 2.4 volts/cell. May be preset to customer's specification for battery type.
- Continuous - 100% duty cycle.
- Low voltage start: will start a deeply discharged battery with low terminal voltage.
- Reverse polarity and short circuit proof.
- Aluminum case.
- Not intended for use as a DC power supply.
- AC Input 115/230 volts, 50 or 60Hz Input voltage selection by switch.

See inside back cover for power equipment adapters



Model JAC2024H Shown

AC Input Current:

JAC2512	12 AMPS @ 120 VOLTS
JAC2024H	11 AMPS @ 115 VOLTS
JAC3024	14 AMPS @ 120 VOLTS

JAC2512	25 AMPS	12 VOLTS	10" w x 7.5" h x 3" d
JAC2024H	20 AMPS	24 VOLTS	10" w x 7.5" h x 3" d
JAC3024	30 AMPS	24 VOLTS	16" w x 7.5" h x 3" d

*Special order, high current models require separate branch AC circuit. NOTE: Specify DC connector with order.

NOTE: Chargers available for other currents and voltages, contact factory.